

## SPARK PLUG APPLICATION CHART - 2-CYCLE

### Spark Plug Application Chart - 2-Cycle Outboard

Model		Serial # Range	Standard Spark Plug Mercury Part Number	Standard Spark Plug Manufacturer's No.	Suppressor(resistor) Spark Plug Mercury No.	Suppressor(resistor) Spark Plug Manufacturer's No.	Gap
2.2	USA	8075603 and up	N/A	N/A	33- 19796	NGK BPR6HS-10	.040
2.5		0A855097 and up	33-8M0114743	NGK BP6HS-10	33- 19796	NGK BPR6HS-10	.040
3		0A855097 - 0G710612	N/A	N/A	33- 19796	NGK BPR6HS-10	.040
3.3		0D901217 and up	33-8M0114743	NGK BP6HS-10	33- 19796	NGK BPR6HS-10	.040
3.5	USA	6202173 and up	33-8M0114743	NGK BP6HS-10	33- 19796	NGK BPR6HS-10	.040

# OUTBOARD

OUTBOARD

Model	Serial # Range	Standard Spark Plug Mercury Part Number	Standard Spark Plug Manufacturer's No.	Suppressor(resistor) Spark Plug Mecury No.	Suppressor(resistor) Spark Plug Manufacturer's No.	Gap
3.6	USA 5404657 and up	33-8M0114744	NGK BP7HS-10	33-17719547	NGK BPR7HS-10	.040
3.6	BEL 9252831 and up	33-8M0114744	NGK BP7HS-10	33-17719547	NGK BPR7HS-10	.040
3.6	CAN 7145388 and up	33-8M0114744	NGK BP7HS-10	33-17719547	NGK BPR7HS-10	.040
3.9 (39)	1655013 - 2498135	33-8M0114737	NGK B5HS	N/A	N/A	.025
4 (40)(1 cyl.)	2498136 - 2771621	33-8M0114737	NGK B5HS	N/A	N/A	.030
4 (40)(1 cyl.)	2771622 - 0A809600	33-97182Q	NGK BUHW-2	33-14103Q	NGK BUZHW-2	
4 (40)(2 cyl.) Gnat	BEL 9075839 - 9256980	33-813472	NGK B6HS	33-813472	NGK BR6HS	.050
4 (40)(2 cyl.) Gnat	CAN 7085673 - 7146487	33-813472	NGK B6HS	33-813472	NGK BR6HS	.050
4 (40)(2 cyl.)	USA 5589202 - 5595531	33-8M0114744	NGK BP7HS-10	33-17719547	NGK BPR7HS-10	.040
4 (40)(2 cyl.)	AUS 8065265 - 8068064	33-8M0114744	NGK BP7HS-10	33-17719547	NGK BPR7HS-10	.040
4 (40)(2 cyl.)	BEL 9256981 - 9258280	33-8M0114744	NGK BP7HS-10	33-17719547	NGK BPR7HS-10	.040
4 (40)(2 cyl.)	CAN 7146488 - 7143687	33-8M0114744	NGK BP7HS-10	33-17719547	NGK BPR7HS-10	.040
4 (1 cyl.)	USA 0A809601 and up	33-8M0114744	NGK BP7HS-10	33-17719547	NGK BPR7HS-10	.040
4 (1 cyl.)	BEL 9477830 and up	33-8M0114744	NGK BP7HS-10	33-17719547	NGK BPR7HS-10	.040
4.5 (45)(1 cyl.)	USA 4107220 - 0A809600	33-97182Q	NGK BUHW-2	33-14103Q	NGK BUZHW-2	
4.5 (45)(1 cyl.)	AUS 8026540 and up	33-97182Q	NGK BUHW-2	33-14103Q	NGK BUZHW-2	
4.5 (45)(1 cyl.)	BEL 9072179 - 9477829	33-97182Q	NGK BUHW-2	33-14103Q	NGK BUZHW-2	
4.5 (45)(1 cyl.)	CAN 7045758 and up	33-97182Q	NGK BUHW-2	33-14103Q	NGK BUZHW-2	
5 (1 cyl.)	USA 0A809601 and up	33-8M0114744	NGK BP7HS-10	33-17719547	NGK BPR7HS-10	.040
5 (1 cyl.)	BEL 9477830 and up	33-8M0114744	NGK BP7HS-10	33-17719547	NGK BPR7HS-10	.040
6 (60)	USA 1408611 - 2126763	33-813416	NGK B6S	N/A	N/A	.025
6 (60)	CAN 1958792 - 2096170	33-813416	NGK B6S	N/A	N/A	.025
6 (60)(60J)	USA 2126764 and up	33-813472	NGK B6HS	33-813472	NGK BR6HS	.030
6 (60)(60J)	CAN 2096171 and up	33-813472	NGK B6HS	33-813472	NGK BR6HS	.030
6	USA 0A197112 - 0T800749	33-816737Q	NGK BP8H-N-10	33-816837Q	NGK BPZ8H-N-10	.040
6	BEL 9461526 and up	33-816737Q	NGK BP8H-N-10	33-816837Q	NGK BPZ8H-N-10	.040
7.5 (75)	2529895 - 3801457	33-97182Q	NGK BUHW-2	33-14103Q	NGK BUZHW-2	
7.5 (75)	USA 3801458 - 4851692	33-97180Q	NGK BUHW	33-14103550	NGK BUZHW	
7.5 (75)	AUS 8015315 - 8051349	33-97180Q	NGK BUHW	33-14103550	NGK BUZHW	
7.5 (75)	BEL 9043194 - 9181725	33-97180Q	NGK BUHW	33-14103550	NGK BUZHW	
7.5 (75)	CAN 7028598 - 7111897	33-97180Q	NGK BUHW	33-14103550	NGK BUZHW	
7.5 (75)	USA 4851693 - 5226934	33-97182Q	NGK BUHW-2	33-14103Q	NGK BUZHW-2	
7.5 (75)	AUS 8051350 - 8058019	33-97182Q	NGK BUHW-2	33-14103Q	NGK BUZHW-2	
7.5 (75)	BEL 9181726 - 9219255	33-97182Q	NGK BUHW-2	33-14103Q	NGK BUZHW-2	
7.5 (75)	CAN 7111898 - 7136037	33-97182Q	NGK BUHW-2	33-14103Q	NGK BUZHW-2	
7.5	USA 5206550 and up	33-813418	NGK B9HS-10	33-813418	NGK BR9HS-10	.040
7.5	AUS 8057545 and up	33-813418	NGK B9HS-10	33-813418	NGK BR9HS-10	.040
7.5	BEL 9217756 and up	33-813418	NGK B9HS-10	33-813418	NGK BR9HS-10	.040
7.5	CAN 7125388 and up	33-813418	NGK B9HS-10	33-813418	NGK BR9HS-10	.040
8	USA 0A197112 and up	33-816737Q	NGK BP8H-N-10	33-816837Q	NGK BPZ8H-N-10	.040
8	BEL 9461526 and up	33-816737Q	NGK BP8H-N-10	33-816837Q	NGK BPZ8H-N-10	.040
9.8 (110)	1470349 - 2098351	33-813416	NGK B6S	N/A	N/A	.025
9.8 (110)	2098352 - 2798056	33-8M0114739	NGK B7HS	N/A	N/A	.030
9.8 (110)	2798057 - 3795657	33-97182Q	NGK BUHW-2	33-14103Q	NGK BUZHW-2	
9.8 (110)	USA 3795658 - 4839253	33-97180Q	NGK BUHW	33-14103550	NGK BUZHW	
9.8 (110)	AUS 8015040 - 8050624	33-97180Q	NGK BUHW	33-14103550	NGK BUZHW	
9.8 (110)	BEL 9041439 - 9165304	33-97180Q	NGK BUHW	33-14103550	NGK BUZHW	
9.8 (110)	CAN 7027323 - 7111347	33-97180Q	NGK BUHW	33-14103550	NGK BUZHW	
9.8 (110)	USA 4839254 - 5206549	33-97182Q	NGK BUHW-2	33-14103Q	NGK BUZHW-2	
9.8 (110)	AUS 8050625 - 8057544	33-97182Q	NGK BUHW-2	33-14103Q	NGK BUZHW-2	
9.8 (110)	BEL 9165303 - 9217755	33-97182Q	NGK BUHW-2	33-14103Q	NGK BUZHW-2	
9.8 (110)	CAN 7111348 - 7125387	33-97182Q	NGK BUHW-2	33-14103Q	NGK BUZHW-2	

Model	Serial # Range	Standard Spark Plug Mercury Part Number	Standard Spark Plug Manufacturer's No.	Suppressor(resistor) Spark Plug Mercury No.	Suppressor(resistor) Spark Plug Manufacturer's No.	Gap	
9.8	USA	5206550 and up	33-813418	NGK B9HS-10	33-813418	NGK BR9HS-10	.040
9.8	AUS	8057545 and up	33-813418	NGK B9HS-10	33-813418	NGK BR9HS-10	.040
9.8	BEL	9217756 and up	33-813418	NGK B9HS-10	33-813418	NGK BR9HS-10	.040
9.8	CAN	7125388 and up	33-813418	NGK B9HS-10	33-813418	NGK BR9HS-10	.040
9.9	USA	0A197112 - 0G112449	33-816737Q	NGK BP8H-N-10	33-816837Q	NGK BPZ8H-N-10	.040
9.9	BEL	9461526 - 9831799	33-816737Q	NGK BP8H-N-10	33-816837Q	NGK BPZ8H-N-10	.040
9.9	USA	0G112450 and up	33-8M0114746	NGK BP8HS-15	33-14814568	NGK BPZ8HS-15	.060
9.9	BEL	9831800 and up	33-8M0114746	NGK BP8HS-15	33-14814568	NGK BPZ8HS-15	.060
10 (100)		1290910 - 1499331	33-813416	NGK B6S	N/A	N/A	.025
10 (XR10/SEA PRO 10)	USA	0D038000 and up	33-8M0114746	NGK BP8HS-15	33-14814568	NGK BPZ8HS-15	.060
10 (XR10/SEA PRO 10)	BEL	9596000 and up	33-8M0114746	NGK BP8HS-15	33-14814568	NGK BPZ8HS-15	.060
10 Magnum/Marathon	USA	0D038000 and up	33-8M0114746	NGK BP8HS-15	33-14814568	NGK BPZ8HS-15	.060
10 Magnum/Marathon	BEL	9596000 and up	33-8M0114746	NGK BP8HS-15	33-14814568	NGK BPZ8HS-15	.060
15 (150)		1290910 - 1499331	33-813416	NGK B6S	N/A	N/A	.025
15	USA	0B292414 and up	33-8M0114746	NGK BP8HS-15	33-14814568	NGK BPZ8HS-15	.060
15	BEL	9542620 and up	33-8M0114746	NGK BP8HS-15	33-14814568	NGK BPZ8HS-15	.060
15 Sea Pro/Marathon	USA	0G044365 - 0G437999	33-816737Q	NGK BP8H-N-10	33-816837Q	NGK BPZ8H-N-10	.040
15 Sea Pro/Marathon	USA	0G438000 and up	33-8M0114746	NGK BP8HS-15	33-14814568	NGK BPZ8HS-15	.060
15 Sea Pro/Marathon	BEL	9927000 and up	33-8M0114746	NGK BP8HS-15	33-14814568	NGK BPZ8HS-15	.060
15 Sea Pro XD	BEL	9927000 and up	33-816737Q	NGK BP8H-N-10	33-816837Q	NGK BPZ8H-N-10	.040
15 (Super 15)	USA	0B238464 and up	33-816737Q	NGK BP8H-N-10	33-816837Q	NGK BPZ8H-N-10	.040
15 (Super 15)	BEL	9507381 and up	33-816737Q	NGK BP8H-N-10	33-816837Q	NGK BPZ8H-N-10	.040
15 (Super 15)	CAN	0A730007 and up	33-816737Q	NGK BP8H-N-10	33-816837Q	NGK BPZ8H-N-10	.040
18 (18, 18XD)	USA	5837437 and up	33-816737Q	NGK BP8H-N-10	33-816837Q	NGK BPZ8H-N-10	.040
18 (18, 18XD)	AUS	8071973 and up	33-816737Q	NGK BP8H-N-10	33-816837Q	NGK BPZ8H-N-10	.040
18 (18, 18XD)	BEL	9308306 and up	33-816737Q	NGK BP8H-N-10	33-816837Q	NGK BPZ8H-N-10	.040
20 (200)		1290910 - 1499331	33-813416	NGK B6S	N/A	N/A	.025
20 (200)		1558310 - 2094830	33-813416	NGK B6S	N/A	N/A	.025
20 (200)		2094831 - 2827676	33-8M0114739	NGK B7HS	N/A	N/A	.030
20 (20, 200)	USA	2827677 - 6443972	33-97182Q	NGK BUHW-2	33-14103Q	NGK BUZHW-2	
20 (20, 200)	AUS	8006265 and up	33-97182Q	NGK BUHW-2	33-14103Q	NGK BUZHW-2	
20 (20, 200)	BEL	9016254 - 9415100	33-97182Q	NGK BUHW-2	33-14103Q	NGK BUZHW-2	
20 (20, 200)	CAN	7012358 - 7209532	33-97182Q	NGK BUHW-2	33-14103Q	NGK BUZHW-2	
20 (20, 20XD)	USA	6443973 - 0T800749	33-816737Q	NGK BP8H-N-10	33-816837Q	NGK BPZ8H-N-10	.040
20 (20, 20XD)	BEL	9415101 and up	33-816737Q	NGK BP8H-N-10	33-816837Q	NGK BPZ8H-N-10	.040
20 (20, 20XD)	CAN	7209533 and up	33-816737Q	NGK BP8H-N-10	33-816837Q	NGK BPZ8H-N-10	.040
20 JET	USA	5705532 and up	33-816737Q	NGK BP8H-N-10	33-816837Q	NGK BPZ8H-N-10	.040
20 JET	AUS	8073158 and up	33-816737Q	NGK BP8H-N-10	33-816837Q	NGK BPZ8H-N-10	.040
20 JET	BEL	9315316 and up	33-816737Q	NGK BP8H-N-10	33-816837Q	NGK BPZ8H-N-10	.040
20 JET	CAN	7166928 and up	33-816737Q	NGK BP8H-N-10	33-816837Q	NGK BPZ8H-N-10	.040
25 (250)		1290910 - 1499331	33-813416	NGK B6S	N/A	N/A	.025
25 (25, 25XD, 20 JET)	USA	5705532 and up	33-816737Q	NGK BP8H-N-10	33-816837Q	NGK BPZ8H-N-10	.040
25 (25, 25XD, 20 JET)	AUS	8073158 and up	33-816737Q	NGK BP8H-N-10	33-816837Q	NGK BPZ8H-N-10	.040
25 (25, 25XD, 20 JET)	BEL	9315316 and up	33-816737Q	NGK BP8H-N-10	33-816837Q	NGK BPZ8H-N-10	.040
25 (25, 25XD, 20 JET)	CAN	7166928 and up	33-816737Q	NGK BP8H-N-10	33-816837Q	NGK BPZ8H-N-10	.040
25 LIGHTNING(3 cyl)	USA	0E268781 and up	33-896323	Champion L82C	33-896329874	Champion RL82C	.035
30 (300)		1271884 - 1960826	33-813416	NGK B6S	N/A	N/A	.025
30 (2 cyl.)644cc	USA	0G053314 - 0T598999	33-816737Q	NGK BP8H-N-10	33-816837Q	NGK BPZ8H-N-10	.040
30 (2 cyl.)644cc	BEL	9854537 - 0P206999	33-816737Q	NGK BP8H-N-10	33-816837Q	NGK BPZ8H-N-10	.040
30 (Lightning)430cc	USA	0G575500 and up	33-828942	NGK B7HS-10	33-828942	NGK BR7HS-10	.040
30 JET (4 cylinder)	USA	0C159200 - 0G589999	33-97182Q	NGK BUHW-2	33-14103Q	NGK BUZHW-2	
30 JET (4 cylinder)	BEL	9570790 - 9973099	33-97182Q	NGK BUHW-2	33-14103Q	NGK BUZHW-2	
30 JET (3 cylinder)	USA	0G590000 - 0T178499	33-816737Q	NGK BP8H-N-10	33-816837Q	NGK BPZ8H-N-10	.040
30 JET (3 cylinder)	BEL	9973100 - 0P094499	33-816737Q	NGK BP8H-N-10	33-816837Q	NGK BPZ8H-N-10	.040
35 (350, 35A)		1271884 - 1960826	33-813416	NGK B6S	N/A	N/A	.025

# OUTBOARD

Model	Serial # Range	Standard Spark Plug Mercury Part Number	Standard Spark Plug Manufacturer's No.	Suppressor(resistor) Spark Plug Mercury No.	Suppressor(resistor) Spark Plug Manufacturer's No.	Gap
35 (350)	1960827 - 2097831	33-813413	NGK B7S	N/A	N/A	.025
35 (350)	2097832 - 2874703	33-8M0114739	NGK B7HS	N/A	N/A	.030
35	USA 6445653 and up	33-97180Q	NGK BUHW	33-14103550	NGK BUZHW	
35	BEL 9384476 and up	33-97180Q	NGK BUHW	33-14103550	NGK BUZHW	
35	CAN 7209608 and up	33-97180Q	NGK BUHW	33-14103550	NGK BUZHW	
40 (400)	1279685 - 1476509	33-813416	NGK B6S	N/A	N/A	.025
40 (40, 400, 402)	USA 2874704 - 0G053313	33-97180Q	NGK BUHW	33-14103550	NGK BUZHW	
40 (40, 400, 402)	AUS 8002335 and up	33-97180Q	NGK BUHW	33-14103550	NGK BUZHW	
40 (40, 400, 402)	BEL 3339688 and up	33-97180Q	NGK BUHW	33-14103550	NGK BUZHW	
40 (40, 400, 402)	CAN 3340783 and up	33-97180Q	NGK BUHW	33-14103550	NGK BUZHW	
40 (2 cyl.)	USA 0G053314 and up	33-816737Q	NGK BP8H-N-10	33-816837Q	NGK BPZ8H-N-10	.040
40 (3 cyl.)	USA 0G531301 and up	33-816737Q	NGK BP8H-N-10	33-816837Q	NGK BPZ8H-N-10	.040
40 (3 cyl.)	BEL 9973100 and up	33-816737Q	NGK BP8H-N-10	33-816837Q	NGK BPZ8H-N-10	.040
40 (4 cyl.)	USA 0C159200 and up	33-97182Q	NGK BUHW-2	33-14103Q	NGK BUZHW-2	
40 (4 cyl.)	BEL 9570790 and up	33-97182Q	NGK BUHW-2	33-14103Q	NGK BUZHW-2	
40 JET	USA 0T178500 and up	33-816737Q	NGK BP8H-N-10	33-816837Q	NGK BPZ8H-N-10	.040
40 JET	BEL 0P094500 and up	33-816737Q	NGK BP8H-N-10	33-816837Q	NGK BPZ8H-N-10	.040
45 (450)	1476510 - 1531568	33-813416	NGK B6S	N/A	N/A	.025
45 (4 cyl.)	USA 5531630 and up	33-97182Q	NGK BUHW-2	33-14103Q	NGK BUZHW-2	
45 (4 cyl.)	AUS 8063985 and up	33-97182Q	NGK BUHW-2	33-14103Q	NGK BUZHW-2	
45 (4 cyl.)	BEL 9248006 and up	33-97182Q	NGK BUHW-2	33-14103Q	NGK BUZHW-2	
45 (4 cyl.)	CAN 7143688 and up	33-97182Q	NGK BUHW-2	33-14103Q	NGK BUZHW-2	
45 JET	USA 0G760300 - 0T129554	33-816737Q	NGK BP8H-N-10	33-816837Q	NGK BPZ8H-N-10	.040
45 JET	BEL 0P017000 - 0P094499	33-816737Q	NGK BP8H-N-10	33-816837Q	NGK BPZ8H-N-10	.040
50 (500)	USA 1421113 - 2097444	33-813416	NGK B6S	N/A	N/A	.025
50 (500)	CAN 1770179 - 2116317	33-813416	NGK B6S	N/A	N/A	.025
50 (500)	USA 2097445 - 4357639	33-97180Q	NGK BUHW	33-14103550	NGK BUZHW	
50 (500)	AUS 2863739 - 8029514	33-97180Q	NGK BUHW	33-14103550	NGK BUZHW	
50 (500)	BEL 9001581 - 9107213	33-97180Q	NGK BUHW	33-14103550	NGK BUZHW	
50 (500)	CAN 2116318 - 7068997	33-97180Q	NGK BUHW	33-14103550	NGK BUZHW	
50 (50, 500)(4 cyl.)	USA 4357640 and up	33-97182Q	NGK BUHW-2	33-14103Q	NGK BUZHW-2	
50 (50, 500)(4 cyl.)	AUS 8030090 and up	33-97182Q	NGK BUHW-2	33-14103Q	NGK BUZHW-2	
50 (50, 500)(4 cyl.)	BEL 9107214 and up	33-97182Q	NGK BUHW-2	33-14103Q	NGK BUZHW-2	
50 (50, 500)(4 cyl.)	CAN 7068998 and up	33-97182Q	NGK BUHW-2	33-14103Q	NGK BUZHW-2	
50 (3 cyl.)	USA 6428681 - 0D000749	33-97180Q	NGK BUHW	33-14103550	NGK BUZHW	
50 (3 cyl.)	BEL 9385911 - 9683054	33-97180Q	NGK BUHW	33-14103550	NGK BUZHW	
50 (3 cyl.)	CAN 7208333 and up	33-97180Q	NGK BUHW	33-14103550	NGK BUZHW	
50 (3 cyl.)	USA 0D000750 and up	33-816737Q	NGK BP8H-N-10	33-816837Q	NGK BPZ8H-N-10	.040
50 (3 cyl.)	BEL 9683055 and up	33-816737Q	NGK BP8H-N-10	33-816837Q	NGK BPZ8H-N-10	.040
55 (3 cyl.)	USA 0D000750 and up	33-816737Q	NGK BP8H-N-10	33-816837Q	NGK BPZ8H-N-10	.040
55 (3 cyl.)	BEL 9741042 and up	33-816737Q	NGK BP8H-N-10	33-816837Q	NGK BPZ8H-N-10	.040
60 (600)	1303411 - 1542744	33-813416	NGK B6S	N/A	N/A	.025
60 (3 cyl.)	USA 6428681 - 0D000749	33-97180Q	NGK BUHW	33-14103550	NGK BUZHW	
60 (3 cyl.)	BEL 9385911 - 9683054	33-97180Q	NGK BUHW	33-14103550	NGK BUZHW	
60 (3 cyl.)	CAN 7208333 and up	33-97180Q	NGK BUHW	33-14103550	NGK BUZHW	
60 (3 cyl.)	USA 0D000750 and up	33-816737Q	NGK BP8H-N-10	33-816837Q	NGK BPZ8H-N-10	.040
60 (3 cyl.)	BEL 9683055 and up	33-816737Q	NGK BP8H-N-10	33-816837Q	NGK BPZ8H-N-10	.040
65 (650)(4 cyl.)	1542745 - 2119748	33-813413	NGK B7S	N/A	N/A	.025
65 (650S)(4 cyl.)	2119749 - 2309310	33-8M0114739	NGK B7HS	N/A	N/A	.030
65 (650SS)(4 cyl.)	2119749 - 2309310	33-97180Q	NGK BUHW	33-14103550	NGK BUZHW	
65 (650)(3 cyl.)	USA 3293184 - 4571651	33-97180Q	NGK BUHW	33-14103550	NGK BUZHW	
65 (650)(3 cyl.)	AUS 8006640 and up	33-97180Q	NGK BUHW	33-14103550	NGK BUZHW	
65 (650)(3 cyl.)	BEL 9020074 - 9135824	33-97180Q	NGK BUHW	33-14103550	NGK BUZHW	
65 (650)(3 cyl.)	CAN 7013633 - 7087822	33-97180Q	NGK BUHW	33-14103550	NGK BUZHW	
65 JET	USA 0D283222 and up	33-97182Q	NGK BUHW-2	33-14103Q	NGK BUZHW-2	
65 JET	BEL 9793577 and up	33-97182Q	NGK BUHW-2	33-14103Q	NGK BUZHW-2	

Model	Serial # Range	Standard Spark Plug Mercury Part Number	Standard Spark Plug Manufacturer's No.	Suppressor(resistor) Spark Plug Mercury No.	Suppressor(resistor) Spark Plug Manufacturer's No.	Gap
70 (700)	1296411 - 1566239	33-813416	NGK B6S	N/A	N/A	.025
70 (3 cyl.)	USA 4571652 - 6428680	33-97180Q	NGK BUHW	33-14103550	NGK BUZHW	
70 (3 cyl.)	AUS 8042350 and up	33-97180Q	NGK BUHW	33-14103550	NGK BUZHW	
70 (3 cyl.)	BEL 9135825 - 9385910	33-97180Q	NGK BUHW	33-14103550	NGK BUZHW	
70 (3 cyl.)	CAN 7087823 - 7208332	33-97180Q	NGK BUHW	33-14103550	NGK BUZHW	
70 (3 cyl.)	USA 0A996142 - 0C221999	33-97182Q	NGK BUHW-2	33-14103Q	NGK BUZHW-2	
70 (3 cyl.)	BEL 9483121 - 9589038	33-97182Q	NGK BUHW-2	33-14103Q	NGK BUZHW-2	
75 (4 cyl.)	USA 6432907 and up	33-97182Q	NGK BUHW-2	33-14103Q	NGK BUZHW-2	
75 (4 cyl.)	BEL 9393856 and up	33-97182Q	NGK BUHW-2	33-14103Q	NGK BUZHW-2	
75 (4 cyl.)	CAN 7208573 and up	33-97182Q	NGK BUHW-2	33-14103Q	NGK BUZHW-2	
75 (3 cyl.)	USA 0C222000 and up	33-97182Q	NGK BUHW-2	33-14103Q	NGK BUZHW-2	
75 (3 cyl.)	BEL 9589039 and up	33-97182Q	NGK BUHW-2	33-14103Q	NGK BUZHW-2	
75 (3 cyl.)(1.5L Optimax)	USA 0T980000 and up	N/A	N/A	33-892567Q	NGK IZFR5J	.032
80 (800)(6 cyl.)	1335465 - 1566239	33-813413	NGK B7S	N/A	N/A	.025
80 (800)(4 cyl.)	2559001 - 3493912	33-97180Q	NGK BUHW	33-14103550	NGK BUZHW	
80 (80, 800)(4 cyl.)	USA 4831999 - 6432900	33-97182Q	NGK BUHW-2	33-14103Q	NGK BUZHW-2	
80 (80, 800)(4 cyl.)	AUS 8050200 and up	33-97182Q	NGK BUHW-2	33-14103Q	NGK BUZHW-2	
80 (80, 800)(4 cyl.)	BEL 9177626 - 9393855	33-97182Q	NGK BUHW-2	33-14103Q	NGK BUZHW-2	
80 (80, 800)(4 cyl.)	CAN 7110998 - 7208572	33-97182Q	NGK BUHW-2	33-14103Q	NGK BUZHW-2	
80 (3 cyl.)	USA 0A996142 - 0C221999	33-97182Q	NGK BUHW-2	33-14103Q	NGK BUZHW-2	
80 (3 cyl.)	BEL 9483121 - 9589038	33-97182Q	NGK BUHW-2	33-14103Q	NGK BUZHW-2	
80 JET	USA 0D283222 and up	33-816737Q	NGK BP8H-N-10	33-816837Q	NGK BPZ8H-N-10	.040
80 JET	BEL 9793577 and up	33-816737Q	NGK BP8H-N-10	33-816837Q	NGK BPZ8H-N-10	.040
85 (850)(6 cyl.)	1460999 - 1766823	33-813413	NGK B7S	N/A	N/A	.025
85 (850)(4 cyl.)	USA 3493913 - 4831998	33-97180Q	NGK BUHW	33-14103550	NGK BUZHW	
85 (850)(4 cyl.)	AUS 8005440 - 8050199	33-97180Q	NGK BUHW	33-14103550	NGK BUZHW	
85 (850)(4 cyl.)	BEL 9011604 - 9177625	33-97180Q	NGK BUHW	33-14103550	NGK BUZHW	
85 (850)(4 cyl.)	CAN 7010108 - 7110997	33-97180Q	NGK BUHW	33-14103550	NGK BUZHW	
90 (900)	1766824 - 1869775	33-813413	NGK B7S	N/A	N/A	.025
90 (90, 900)(6 cyl.)	USA 4845301 and up	33-97180Q	NGK BUHW	33-14103550	NGK BUZHW	
90 (90, 900)(6 cyl.)	AUS 8060545 and up	33-97180Q	NGK BUHW	33-14103550	NGK BUZHW	
90 (90, 900)(6 cyl.)	CAN 7111698 and up	33-97180Q	NGK BUHW	33-14103550	NGK BUZHW	
90 (3 cyl.)	USA 0A996142 and up	33-97182Q	NGK BUHW-2	33-14103Q	NGK BUZHW-2	
90 (3 cyl.)	BEL 9483121 and up	33-97182Q	NGK BUHW-2	33-14103Q	NGK BUZHW-2	
90 (3 cyl.)(1.5L Optimax)	USA 0T801000 and up	N/A	N/A	33-892567Q	NGK IZFR5J	.032
95 (950)	1869776 - 1962186	33-8M0114739	NGK B7HS	N/A	N/A	.030
95 (950)	1962187 - 2318585	33-97180Q	NGK BUHW	33-14103550	NGK BUZHW	
100 (1000)	1464949 - 2318585	33-813413	NGK B7S	N/A	N/A	.025
100 (1000SS/1000BP)	2318586 - 3253111	33-97180Q	NGK BUHW	33-14103550	NGK BUZHW	
100 (4 cyl.)	USA 0B209468 - 0G960499	33-816737Q	NGK BP8H-N-10	33-816837Q	NGK BPZ8H-N-10	.040
100 (4 cyl.)	BEL 9523034 - 0P058999	33-816737Q	NGK BP8H-N-10	33-816837Q	NGK BPZ8H-N-10	.040
110 (1100)	1870204 - 1962661	33-8M0114739	NGK B7HS	N/A	N/A	.030
110 (1100)	1962662 - 2314955	33-97180Q	NGK BUHW	33-14103550	NGK BUZHW	
115 (115, 1150)(6 cyl.)	USA 2836019 and up	33-97180Q	NGK BUHW	33-14103550	NGK BUZHW	
115 (115, 1150)(6 cyl.)	AUS 8008665 and up	33-97180Q	NGK BUHW	33-14103550	NGK BUZHW	
115 (115, 1150)(6 cyl.)	CAN 7010763 and up	33-97180Q	NGK BUHW	33-14103550	NGK BUZHW	
115 (4 cyl.)	USA 0C100000 and up	33-816737Q	NGK BP8H-N-10	33-816837Q	NGK BPZ8H-N-10	.040
115 (4 cyl.)	BEL 9559771 and up	33-816737Q	NGK BP8H-N-10	33-816837Q	NGK BPZ8H-N-10	.040
115 (3 cyl.)(1.5L Optimax)	USA 0T801000 and up	N/A	N/A	33-892567Q	NGK IZFR5J	.032
115 Pro XS	USA 1B751825 and up	N/A	N/A	33-892567Q	NGK IZFR5J	.032
125 (1250)(6 cyl.)	2314956 - 3253111	33-97180Q	NGK BUHW	33-14103550	NGK BUZHW	
125 (4 cyl.)	USA 0D283222 and up	33-816737Q	NGK BP8H-N-10	33-816837Q	NGK BPZ8H-N-10	.040
125 (4 cyl.)	BEL 9793577 and up	33-816737Q	NGK BP8H-N-10	33-816837Q	NGK BPZ8H-N-10	.040
135 (1350)(6 cyl.)	2839369 - 3293233	33-97180Q	NGK BUHW	33-14103550	NGK BUZHW	
140 (140, 1400)(6 cyl.)	USA 3293234 and up	33-97180Q	NGK BUHW	33-14103550	NGK BUZHW	
140 (140, 1400)(6 cyl.)	AUS 8052650 and up	33-97180Q	NGK BUHW	33-14103550	NGK BUZHW	

# OUTBOARD

Model	Serial # Range	Standard Spark Plug Mercury Part Number	Standard Spark Plug Manufacturer's No.	Suppressor(resistor) Spark Plug Mercury No.	Suppressor(resistor) Spark Plug Manufacturer's No.	Gap
140 (140, 1400)(6 cyl.)	CAN 7112773 and up	33- 97180Q	NGK BUHW	33- 14103550	NGK BUZHW	
150 (1500)(6 cyl.)	USA 3502806 - 4865677	33- 97180Q	NGK BUHW	33- 14103550	NGK BUZHW	
150 (1500)(6 cyl.)	AUS 8005615 - 8052649	33- 97180Q	NGK BUHW	33- 14103550	NGK BUZHW	
150 (1500)(6 cyl.)	CAN 7010533 - 7112772	33- 97180Q	NGK BUHW	33- 14103550	NGK BUZHW	
V-135	USA 0A904646 and up	33- 13686Q	NGK BU8H	33- 14103568	NGK BUZ8H	
V-135 DFI	USA 0G590000 and up	N/A	N/A	33- 889597Q	NGK IZFR5G	.032
V-150 (150, 1500) Carb	USA 4868998 - 0G960499	33- 13686Q	NGK BU8H	33- 14103568	NGK BUZ8H	
V-150 (150, 1500) Carb	USA 0G960500 and up	N/A	N/A	33- 14814Q	NGK BPZ8HS-10	.040
V-150 EFI	USA 0D082000 - 0G960499	33- 13686Q	NGK BU8H	33- 14103568	NGK BUZ8H	
V-150 EFI	USA 0G960500 and up	N/A	N/A	33- 14814Q	NGK BPZ8HS-10	.040
V-150 (XR2/4/6/Magnum II/III)	USA 4868998 - 0G960499	33- 13686Q	NGK BU8H	33- 14103568	NGK BUZ8H	
V-150 (XR2/4/6/Magnum II/III)	USA 0G960500 and up	N/A	N/A	33- 14814Q	NGK BPZ8HS-10	.040
V-150 DFI	USA 0G590000 and up	N/A	N/A	33- 889597Q	NGK IZFR5G	.032
V-150 ProXS	USA 1B690542 and up	N/A	N/A	33- 843220Q	NGK IZFR6J	.042
V-175 (175, 1750) Carb	USA 4301235 - 0G960499	33- 13686Q	NGK BU8H	33- 14103568	NGK BUZ8H	
V-175 (175, 1750) Carb	AUS 8058870 and up	33- 13686Q	NGK BU8H	33- 14103568	NGK BUZ8H	
V-175 EFI	USA 0D000750 - 0G960499	33- 13686Q	NGK BU8H	33- 14103568	NGK BUZ8H	
V-175 EFI	USA 0G960500 - 0T800999	N/A	N/A	33- 14814Q	NGK BPZ8HS-10	.040
V-175 DFI	USA 0T178500 and up	N/A	N/A	33- 889597Q	NGK IZFR5G	.032
V-175 Pro XS	USA 1B516339 and up	N/A	N/A	33- 843220Q	NGK IZFR6J	.042
V-200 (200, 2000) Carb	USA 4839034 - 0G960499	33- 13686Q	NGK BU8H	33- 14103568	NGK BUZ8H	
V-200 (200, 2000) Carb	AUS 8061595 - 8065672	33- 13686Q	NGK BU8H	33- 14103568	NGK BUZ8H	
V-200 (200, 2000) Carb	USA 0G960500 and up	N/A	N/A	33- 14814Q	NGK BPZ8HS-10	.040
V-200 EFI	USA 0C100861 - 0C291520	N/A	N/A	33- 14103568	NGK BUZ8H	
V-200 EFI	USA 0C291521 - 0G960499	33- 13686Q	NGK BU8H	33- 14103568	NGK BUZ8H	
V-200 EFI (2.5L)	USA 0G960500 and up	N/A	N/A	33- 14814Q	NGK BPZ8HS-10	.040
V-200 EFI (3.0L)	USA 0T750164 and up	N/A	N/A	33- 941	Champion QL77CC	.040
V-200 DFI	USA 0G386496 and up	N/A	N/A	33- 889597Q	NGK IZFR5G	.032
V-200 Pro XS	USA 1B504989 and up	N/A	N/A	33- 889597Q	NGK IZFR5G	.032
V-220 Laser	USA 0B117316 and up	N/A	N/A	33- 14103568	NGK BUZ8H	
V-225 (2.4L)	USA 5628028 and up	33- 13686Q	NGK BU8H	33- 14103568	NGK BUZ8H	
V-225 (3.0L)Carb	USA 0D280813 - 0G437999	N/A	N/A	33- 816837Q	NGK BPZ8H-N-10	.040
V-225 (3.0L)Carb	USA 0G438000 and up	N/A	N/A	33- 941	Champion QL77CC	.035
V-225 Sea Pro & Marathon	USA 0G245605 and up	N/A	N/A	33- 941	Champion QL77CC	.035
V-225 EFI(3.0L)	USA 0G129222 and up	N/A	N/A	33- 941	Champion QL77CC	.035
V-225 DFI	USA 0G590000 and up	N/A	N/A	33- 889597Q	NGK IZFR5G	.032
V-225 DFI (DTS)	USA 0G599000 and up	N/A	N/A	33- 889597Q	NGK IZFR5G	.032
V-225 Pro XS	USA 1B104549 and up	N/A	N/A	33- 843220Q	NGK IZFR6J	.042
V-250 (3.4L)	USA 0C101891 and up	33- 13686Q	NGK BU8H	33- 14103568	NGK BUZ8H	
V-250 EFI (3.0L)	USA 0G129222 and up	N/A	N/A	33- 941	Champion QL77CC	.035
V-250 DFI (3.0L)	USA 1B528615 and up	N/A	N/A	33- 843220Q	NGK IZFR6J	.042
V-250 Pro XS	USA 1B426561 and up	N/A	N/A	33- 843220Q	NGK IZFR6J	.042
V-275 (3.4L)	USA 0C101891 and up	33- 13686Q	NGK BU8H	33- 14103568	NGK BUZ8H	
V-300 (3.4L)	USA 5611648 and up	33- 13686Q	NGK BU8H	33- 14103568	NGK BUZ8H	